

FE 8100



FE 8100

Wireless receiver

- Receives the radio signals from up to 8 STEINEL transmitters
- Switches the plugged-in load "ON" and "OFF" automatically



Technical Data FE 8100

Prod.-No.:	black 705114
Prod.-No.:	white 705510
Dimensions (h x w x d)	110 x 75.5 x 43 mm
Operating voltage / mains connection	230-V mains power supply
Enclosure	IP 54
Switching capacity	1000 W max. (resistive load, e.g. filament bulb) 500 W max. (uncorrected, inductive, $\cos \theta = 0.5$, e.g. fluorescent lamps)
Operating frequency	863,3 MHz (ISM-Band)
Programming	at the press of a button / capability of programming up to 8 different transmitters
Special features	For installation indoors and outdoors Subject to technical modifications