

NF 50 UP



The NF 50 UP close-range sensor switches light "ON" or "OFF" without touching. Ideal for kitchens, bathrooms, workshops, practices and all rooms where the emphasis is on hygiene, cleanliness and electrical safety.

The NF 50 SensorSwitch is equipped with a close-range sensor that responds to hand movements close up to the sensor (within a distance of 5 cm). This makes it possible to operate lights safely in work environments, even with wet or dirty hands.


- Concealed, close-range sensor, ideal for kitchens, bathrooms, workshops and practices

This is how it works

- Switches "ON" and "OFF" without touching
- A light-emitting diode allows you to locate the SensorSwitch surface even in the dark.




Close-range sensor



Reach

NF 50 UP

Prod. No.	752118
Dimensions (h x w x d)	81 x 81 x 55 mm
Output	1000 W max. (e. g. filament bulbs) 500 VA max. (e. g. fluorescent lamp)
Voltage	230 – 240 V / 50 Hz 3-wire connection (L,L',N) not suitable for use in 2-way circuits
Angle of coverage	at close range
Reach	5 cm max.
Twilight setting	–
Time setting	–
Manual override	–
Permanently OFF	–
LED	Orientation light
Enclosure	IP 20
Protection class	II
Accessories	including 

Subject to technical modifications