

MF 1



MF 1

Wireless module for sensIQ and RS PRO 1000

- Operating convenience for STEINEL receivers (indoors and outdoors)
- Suitable for sensIQ and RS PRO 1000
- Bidirectional (transmitter and receiver)



Technical Data MF 1

Prod.-No.:	white 736712
Dimensions (h x w x d)	75 x 35 x 17 mm
Operating voltage / mains connection	via sensIQ or RS PRO 1000
Transmitter range	up to 100 m with uninterrupted line of vision dia. of 30 m indoors
Operating frequency	863,3 MHz (ISM-Band)
Transmitter power	less than 1000 µW
Programming	at 5-way DIP switch 32 possible addresses per channel
Number of receivers	Any Subject to technical modifications